

AN L^2 -STABILITY ESTIMATE FOR PERIODIC NONUNIFORM SAMPLING IN HIGHER DIMENSIONS

CHRISTINA FREDERICK

ABSTRACT. We consider sampling strategies for a class of multivariate bandlimited functions f that have a spectrum consisting of disjoint frequency bands. Taking advantage of the special spectral structure, we provide formulas relating f to the samples $f(y), y \in X$, where X is a periodic nonuniform sampling set. In this case, we show that the reconstruction can be viewed as an iterative process involving certain Vandermonde matrices, resulting in a link between the invertibility of these matrices to the existence of certain sampling sets that guarantee a unique recovery. Furthermore, estimates of inverse Vandermonde matrices are used to provide explicit L^2 -stability estimates for the reconstruction of this class of functions.

1. INTRODUCTION

Almost all scientific applications that involve processing large datasets or images rely heavily on the acquisition and storage of measurements of a complex physical process or system. Efficiency is gained when the samples contain just enough information to uniquely recover the signal, but no more. As advancements in technology demand more sophisticated methods to handle data, it becomes even more important to understand the fundamental structure of sampling processes. Mathematically, the problem can be formulated as the reconstruction of a function f , in a reliable manner, from knowledge of a collection of its function values, called samples, evaluated at points in a discrete sampling set $X = \{x_j\}$. The celebrated sampling theorem that Shannon used in his theory of communication [12] deals bandlimited functions, $f \in L^2(\mathbb{R})$, whose Fourier transform is contained in a bounded set $\Omega \subset \mathbb{R}$. Shannon's theorem states that f is uniquely determined by its samples taken on the uniform sampling set $X = \{j\Delta \mid j \in \mathbb{Z}\}$, where the spacing Δ must be chosen to resolve the highest frequencies in the spectrum. Moreover, explicit reconstruction formulas are given that relate the samples $f(y), y \in X$ to the desired function f . Sampling of bandlimited functions using arbitrary sampling sets is less understood, especially in higher dimensions, and there is an enormous volume of literature on nonuniform sampling theory and its various generalizations and extensions [1, 7, 10, 11].

In addition to the problem of finding sampling sets that can be used to uniquely determine f , it is important to assess the stability of the reconstruction, or sensitivity with respect to small changes in the sampling set. The set $X \subset \mathbb{R}$ is a stable set of sampling if for some constant $C > 0$,

$$\|f\|_{L_2(\mathbb{R})} \leq C \sum_{y \in X} |f(y)|^2.$$

Explicit estimates of the stability constant for arbitrary sampling sets $X \subset \mathbb{R}^d$ are given in [6], however the proof relies on an upper bound on the maximum distance between a sampling point x_j and its nearest neighbor $x_{j'} \neq x_j$. This upper bound depends on the dimension,

and the given estimates deteriorate in higher dimensions. It is known, however, that the necessary density conditions on the sampling set are independent of dimension [2, 9].

In this paper, we determine the stability constants explicitly by examining properties of matrices that are produced from periodic sampling formulas and applying estimates of inverse Vandermonde matrices. Here, additional conditions on the spectral structure of multivariate bandlimited functions, called multiband functions. These functions are well-studied in the literature on periodic sampling, however stability estimates are rarely given explicitly. In §2, we state the main result and give lemmas needed for the main reconstruction result and estimates of inverse Vandermonde matrices. In §3, an iterative reconstruction algorithm is given. The proof of the main stability result is given in §4.

Notation: The Fourier transform of $f \in L^2(\mathbb{R}^d)$ is given by $\hat{f}(\omega) = \int_{\mathbb{R}^d} f(x) e^{2\pi i x \cdot \omega} dx$, where $x \cdot \xi = \sum_{i=1}^d x_i \omega_i$ is the Euclidean inner product on $\mathbb{R}^d$. Furthermore, we define the norm $\|x\|_\infty = \max_{i=1, \dots, d} |x_i|$ and the Euclidean norm $|x| = (\sum_{i=1}^d |x_i|^2)^{1/2}$. For a bounded set $D \subset \mathbb{R}^d$, the class of D -bandlimited functions is given by $\mathcal{B}(D) = \{f \in L^2(\mathbb{R}^d) \mid \text{supp } \hat{f} \subset D\}$.

2. MAIN RESULT

Motivated by the one-dimensional case presented in [3], the setting here involves multivariate functions that are bandlimited to a set composed of a finite number of nonoverlapping translations of $\Omega = (-1/2, 1/2)^d$. For a nonnegative integer M , the set $\mathcal{M}^d = \mathbb{Z}^d \cap [-M, M]^d$ is taken to be a bounded, discrete set corresponding to the disjoint frequency bands in the spectrum $\Omega_{M,N}$, given by

$$(1) \quad \Omega_{M,N} = \{\xi + mN \mid \xi \in \Omega, m \in \mathcal{M}^d\}, \quad N \geq 1.$$

The left plot in Figure 1 illustrates $\Omega_{M,N}$ in two dimensions.

The main theorem describes the reconstruction of functions $f \in \mathcal{B}(\Omega_{M,N})$ from samples on the periodic nonuniform sampling set determined by the spectrum of f .

Theorem 1. *A function $f \in \mathcal{B}(\Omega_{M,N})$ can be uniquely reconstructed from the periodic nonuniform samples $f(y), y \in X$, where*

$$(2) \quad X = \{j\Delta + k\delta\Delta \mid j, k \in \mathbb{Z}^d, \quad 0 \leq |k| \leq 2M\},$$

with $\frac{1}{N} \leq \Delta \leq 1$ and $0 < \delta \leq \frac{1}{(2M+1)N}$. In addition, the following stability estimate holds:

$$(3) \quad A\|f\|_{L^2(\mathbb{R}^d)}^2 \leq \sum_{y \in X} |f(y)|^2 \leq B\|f\|_{L^2(\mathbb{R}^d)}^2,$$

where the constants A and B satisfy


$$(4) \quad (2M+1)^{-d} \left(\prod_{m=1}^{2M} \sin(m\pi\delta) \right)^{2d} \leq A \leq (2M+1)^d, \quad B = (2M+1)^d.$$

When $N = 1$ and $\delta = 1/(2M+1)$, the uniform sampling set X allows for reconstruction with stability constants

$$(5) \quad A = B = (2M+1)^d.$$

The right plot in Figure 1 provides an illustration of a periodic nonuniform sampling set of the form (2) in two dimensions. Landau proved a lower bound on the sampling rate needed for stable sampling [8]. Applied to periodic nonuniform sampling, this lower bound is

FIGURE 1. On the left is the multiband spectrum given by (1), and on the right is a periodic nonuniform sampling set (2).



$|\Omega_{MN}| = (2M+1)^d$ samples in each interval $[0, 1)^d$. The density of sampling sets in Theorem 1 attains the Landau bound. It should be noted that the lower bound on Δ is not necessary for sampling and reconstruction, however the added restriction removes the possibility of oversampling.

2.1. Subsampling formula. A function f in the space $\mathcal{B}(\Omega_{M,N})$ has the representation

$$(6) \quad f(x) = \sum_{m \in \mathcal{M}^d} c_m(x) e^{2\pi i m N \cdot x}$$

for a set of coefficient functions $c_m \in \mathcal{B}(\Omega)$ that satisfy $\widehat{c_m}(\xi) = \widehat{f}(\xi + mN)$ for $\xi \in \Omega$ and $\widehat{c_m}(\xi) = 0$ otherwise.

Lemma 1. *Let f be a function in $\mathcal{B}(\Omega_{M,N})$ with representation (6). Then, $\|f\|_{L^2(\mathbb{R}^d)}^2 = \sum_{m \in \mathcal{M}^d} \|c_m\|_{L^2(\mathbb{R}^d)}^2$.*

Proof. The proof involves taking the Fourier transform and using the properties of functions $c_m \in \mathcal{B}(\Omega)$,

$$\begin{aligned} \int_{\mathbb{R}^d} |\widehat{f}(\xi)|^2 d\xi &= \int_{\mathbb{R}^d} \left| \sum_{m \in \mathcal{M}^d} \widehat{c_m}(\xi - mN) \right|^2 d\xi \\ &= \sum_{m \in \mathcal{M}^d} \int_{\Omega + mN} |\widehat{c_m}(\xi - mN)|^2 d\xi = \sum_{m \in \mathcal{M}^d} \int_{\mathbb{R}^d} |\widehat{c_m}(\xi)|^2 d\xi. \end{aligned}$$

□

Suppose $Y = X_0 = \{j\Delta \mid j \in \mathbb{Z}^d\}$. The sampling operator S_Y is formally defined for functions $g \in L^2(\mathbb{R}^d)$ by the formula

$$(7) \quad S_Y g(x) = \sum_{y \in Y} g(y) \varphi_s(x - y),$$

$$(8) \quad \varphi_s(z) = \Delta^d \int_{\Omega_s} e^{2\pi i z \cdot \xi} d\xi, \quad \Omega_s = \left(-\frac{1}{2\Delta}, \frac{1}{2\Delta}\right)^d.$$

Since $\widehat{\varphi}_s(\xi) = \Delta^d$ if $\xi \in \Omega_s$ and $\widehat{\varphi}_s = 0$ otherwise, it follows that φ_s is square-integrable and $\|\varphi_s\|_{L^2(\mathbb{R}^d)} = \sqrt{\Delta^d}$. A higher dimensional extension of the classical sampling theorem [1] states that for functions g in the space $\mathcal{B}(\Omega)$, $\Omega \subset \Omega_s$, the function $S_Y g$ is well-defined and $S_Y g = g$. Furthermore, the following stability estimate holds,

$$(9) \quad \|S_Y g\|_{L^2(\mathbb{R}^d)}^2 = \Delta^d \sum_{y \in Y} |g(y)|^2.$$

Since the integer translates of $\frac{1}{\Delta}$ are not necessarily integer multiples of N , we need to introduce the constants $L_m = (L_{m_1}, \dots, L_{m_d}) \in \mathbb{Z}^d$ and $\alpha_m = (\alpha_{m_1}, \dots, \alpha_{m_1}) \in [0, \frac{1}{\Delta}]^d$ that uniquely satisfy for $1 \leq i \leq d$,

$$\begin{aligned} L_{m_i} &= \lfloor m_i N \Delta \rfloor, & \alpha_{m_i} &= m_i N - \frac{\lfloor m_i N \Delta \rfloor}{\Delta} & m_i &\geq 0 \\ L_{m_i} &= -L_{-m_i}, & \alpha_{m_i} &= -\alpha_{-m_i} & m_i &< 0. \end{aligned}$$

Note that $m_i \leq L_{m_i} \leq m_i N$ and $1 \leq L_1 < L_2 < \dots < L_M$ and there is a unique decomposition for each $m \in \mathcal{M}^d$,

$$mN = \frac{L_m}{\Delta} + \alpha_m.$$

Lemma 2. Let $g_m(x) = c_m e^{2\pi i m N \cdot x}$, be the terms in the summation (6), and for $k \in \mathbb{Z}^d$ let $X_k = \{j\Delta + k\delta\Delta \mid j \in \mathbb{Z}^d\}$, where $\frac{1}{N} \leq \Delta \leq 1$ and $\delta > 0$. Then,

$$(10) \quad (S_{X_k} g_m)(x) = \sum_{y \in X_k} c_m(y) e^{2\pi i m N \cdot y} \varphi_s(x - y)$$

is a function in the space $\mathcal{B}(\Omega + \alpha_m)$. Furthermore, the following stability estimate holds:

$$(11) \quad \|S_{X_k} g_m\|_{L^2(\mathbb{R}^d)}^2 = \Delta^d \sum_{y \in X_k} |c_m(y)|^2.$$

Proof. Define the shifted function $d_m(x) = c_m(x + k\delta\Delta) e^{2\pi i m N \cdot k\delta\Delta}$. Then,

$$\begin{aligned} (S_{X_k} g_m)(x) &= \sum_{y \in X_k} c_m(y) e^{2\pi i m N \cdot y} \varphi_s(x - y) \\ (12) \quad &= \sum_{y \in X_0} d_m(y) e^{2\pi i \alpha_m \cdot y} \varphi_s(x - y - k\delta\Delta). \end{aligned}$$

Applying the formula (9), it follows that $\sum_{y \in X_0} |d_m(y)|^2 < \infty$ and therefore

$$\begin{aligned} \|S_{X_k} g_m\|_{L^2(\mathbb{R}^d)}^2 &\leq \int_{\mathbb{R}^d} \sum_{y \in X_0} |d_m(y) \varphi_s(x - y - k\delta\Delta)|^2 dx \\ &\leq \left(\sum_{y \in X_0} |d_m(y)|^2 \right) \|\varphi_s\|_{L^2(\mathbb{R}^d)}^2 < \infty. \end{aligned}$$

Therefore $S_{X_k} g_m$ is a square integrable function. Following from (12),

$$\begin{aligned}
(13) \quad (S_{X_k} g_m)(x) &= \Delta^d \sum_{y \in X_0} d_m(y) e^{2\pi i \alpha_m \cdot y} \int_{\Omega_s} e^{2\pi i (x-y-k\delta\Delta) \cdot \xi} d\xi \\
&= \int_{\Omega_s} \left[\Delta^d \sum_{y \in X_0} d_m(y) e^{-2\pi i (\xi - \alpha_m) \cdot y} \right] e^{2\pi i (x-k\delta\Delta) \cdot \xi} d\xi \\
(14) \quad &= \int_{\Omega_s} \left[\sum_{z \in \Omega_s^{-1}} \widehat{d_m}(\xi - \alpha_m + z) e^{-2\pi i (\xi - \alpha_m) \cdot y} \right] e^{2\pi i (x-k\delta\Delta) \cdot \xi} d\xi \\
(15) \quad &= \int_{\Omega_s} \widehat{d_m}(\xi - \alpha_m) e^{2\pi i (x-k\delta\Delta) \cdot \xi} d\xi \\
&= d_m(x - k\delta\Delta) e^{2\pi i \alpha_m \cdot (x-k\delta\Delta)} \\
(16) \quad &= c_m(x) e^{2\pi i (\alpha_m \cdot x + L_m \cdot k\delta)}.
\end{aligned}$$

The higher dimensional Poisson summation formula with $\Omega_s^{-1} = \{l/\Delta \mid l \in \mathbb{Z}^d\}$ results in (13). Also, since $\Omega \subseteq \Omega_s$, the (up to two) nonzero terms in the summation in (14) have nonoverlapping support, resulting in (15). By taking the Fourier transform, it is clear that the function in the right hand side of (16) is bandlimited to the set $\Omega + \alpha_m$. The stability estimate (11) also follows, since c_m satisfies (9). $\square$

The next lemma describes the reconstruction of functions $f \in \mathcal{B}(\Omega_{M,N})$ and is a generalization of the one-dimensional result in [3].

Lemma 3. *Let f be a function in the space $\mathcal{B}(\Omega_{M,N})$ and let X_k be a sampling set defined in Lemma 2. Then, the function $S_{X_k} f(x) = \sum_{y \in X_k} f(y) \varphi_s(x - y)$ is a function in $\mathcal{B}(\cup_{m \in \mathcal{M}^d} (\Omega + \alpha_m))$. For stability,*

$$(17) \quad \|S_{X_k} f\|_{L^2(\mathbb{R}^d)}^2 \leq \Delta^d \sum_{y \in X_k} |f(y)|^2 \leq \|f\|_{L^2(\mathbb{R}^d)}^2.$$


Proof. Summing the terms (16) over m in the set $\mathcal{M}^d$,

$$\begin{aligned}
\sum_{m \in \mathcal{M}^d} (S_{X_k} c_m e^{2\pi i N m \cdot (\cdot)})(x) &= \sum_{m \in \mathcal{M}^d} \sum_{y \in X_k} c_m(y) e^{2\pi i m N \cdot y} \varphi_s(x - y) \\
&= \sum_{y \in X_k} \sum_{m \in \mathcal{M}^d} c_m(y) e^{2\pi i m N \cdot y} \varphi_s(x - y) \\
&= \sum_{y \in X_k} f(y) \varphi_s(x - y) = S_{X_k} f(x).
\end{aligned}$$

Since $\mathcal{M}^d$ is a finite set, the function $S_{X_k} f(x)$ is a finite sum of square-integrable functions, and is therefore also square-integrable. Then, using (16),

$$(18) \quad S_{X_k} f(x) = \sum_{m \in \mathcal{M}^d} c_m(x) e^{2\pi i (\alpha_m \cdot x + L_m \cdot k\delta)}.$$

FIGURE 2. Distribution of the complex numbers $\omega_{-M}, \dots, \omega_M$ on the unit circle produced by $\omega_m = e^{i\theta_m}$. The blue chords represent the distances in the products in (21).



By the linearity of the Fourier transform, it follows that $f \in \mathcal{B}(\cup_{m \in \mathcal{M}^d} (\Omega + \alpha_m))$. Then, using (9) and Lemma 1,

$$\Delta^d \sum_{y \in X_k} |f(y)|^2 \leq \Delta^d \sum_{y \in X_k} \sum_{m \in \mathcal{M}^d} |c_m(y)|^2 = \|f\|_{L^2(\mathbb{R}^d)}^2,$$

and it follows from the Cauchy-Schwarz inequality that

$$\|S_{X_k} f\|_{L^2(\mathbb{R}^d)}^2 = \left\| \sum_{y \in X_k} f(y) \varphi_s(x - y) \right\|_{L^2(\mathbb{R}^d)}^2 \leq \Delta^d \sum_{y \in X_k} |f(y)|^2.$$

□

2.2. Vandermonde matrix estimates for $d = 1$. In [3], the following result is given for the system of equations (18) in one spatial dimension. We present the proof, reformulated in the present context.

Lemma 4. *Let $d = 1$, and define $\tilde{f} = (S_{X_0} f, \dots, S_{X_P} f)$, where $X_k = \{j\Delta x + k\delta\Delta \mid j \in \mathbb{Z}\}$, where $\frac{1}{N} \leq \Delta \leq 1$ and $0 < \delta \leq 1/(2M+1)N$. The system of equations given by (18) has the form*

$$V\tilde{c} = \tilde{f}, \quad \tilde{c}(x) = (c_{-M}^\alpha(x), \dots, c_M^\alpha(x)),$$

where V is an invertible $(2M+1) \times (2M+1)$ Vandermonde matrix and $c_m^\alpha(x) = c_m(x)e^{2\pi i \alpha_m \cdot x}$. Then,

$$(19) \quad \frac{1}{2M+1} < \|V^{-1}\|_\infty < \prod_{m=1}^{2M} \frac{1}{\sin(m\pi\delta)}.$$

Furthermore, if $N = 1$ and $\delta = \frac{1}{(2M+1)}$, then $\|V_n^{-1}\|_\infty = 1$.

Proof. The the system of equations (18) in the one-dimensional case is understood using properties of $n \times n$ Vandermonde matrices of the form

$$V_n = \begin{pmatrix} 1 & 1 & \dots & 1 \\ \omega_1 & \omega_2 & \dots & \omega_n \\ \omega_1^2 & \omega_2^2 & \dots & \omega_n^2 \\ \vdots & \vdots & \dots & \vdots \\ \omega_1^{n-1} & \omega_2^{n-1} & \dots & \omega_n^{n-1} \end{pmatrix},$$

where $\omega_1, \dots, \omega_n$ are distinct nonzero complex numbers and $n > 1$. A result of Gautschi [5] states that

$$(20) \quad \max_m \prod_{m' \neq m} \frac{1}{|\omega'_m - \omega_m|} < \|V_n^{-1}\|_\infty \leq \max_m \prod_{m' \neq m} \frac{2}{|\omega'_m - \omega_m|}.$$

For $m = -M, \dots, M$, define the unit complex numbers $\omega_m = e^{i\theta_m}$ corresponding to the angles $\theta_m = 2\pi L_m \delta$. Since $0 = \theta_0 < \theta_1 < \dots < \theta_M \leq 2\pi M/(2M+1) < \pi$ are distinct, the $(2M+1) \times (2M+1)$ Vandermonde matrix V with entries $(V)_{jk} = \omega_{(k-M)}^j$ is invertible.

For $N = 1$ and $\delta = \frac{1}{(2M+1)}$, $\theta_m = \frac{m}{2M+1}$ are roots of unity and it is known that $\|V^{-1}\|_\infty = 1$. Otherwise, for $-M \leq m \leq M-1$, it follows that $N = \frac{L_{m+1}-L_m}{\Delta} + (\alpha_{m+1} - \alpha_m) = \frac{L_1}{\Delta} + \alpha_1$. Therefore $L_{m+1} - L_m \geq L_1$ and $|\omega_{m+1} - \omega_m| \geq |\omega_1 - \omega_0|$. Furthermore, $\theta_M + \theta_1/2 = \pi(2M+1)N\delta \leq \pi$ and so $|\omega_M - \omega_{-M}| = |1 - e^{2i\theta_M}| \geq |\omega_1 - \omega_0|$. The product in (20) is maximized when $m = 0$, (see Figure 2 for an illustration) and

$$(21) \quad |\omega_m - \omega_0| = 2|\sin(\theta_m/2)| = 2|\sin(\pi L_m \delta)|.$$

The result (19) follows from the estimate (note $m \leq \lfloor mN\Delta \rfloor \leq mN$),

$$(22) \quad \prod_{m=1}^{2M} \frac{2}{|\omega_m - \omega_0|} = \prod_{m=1}^{2M} \frac{1}{\sin(\lfloor mN\Delta \rfloor \pi \delta)} \leq \prod_{m=1}^{2M} \frac{1}{\sin(m\pi \delta)}.$$

The product of the terms $|\omega_m - \omega_0|$ is minimized if $\delta = 1/(2M+1)N$ and the lower bound is a well-known result for the product of the lengths of the sides of a regular polygon inscribed in the unit circle,

$$(23) \quad \prod_{m=1}^{2M} \frac{1}{|\omega_m - \omega_0|} \geq \prod_{m=1}^{2M} \frac{1}{2|\sin(mN\pi\delta)|} \geq \prod_{m=1}^{2M} \frac{1}{2\sin\left(2\pi\frac{m}{2M+1}\right)} = \frac{1}{2M+1}.$$

The upper bound in (20) is attained if the complex numbers $\omega_m = |\omega_m|e^{i\theta}$ are points on the same ray through the origin. This happens only when $M = 0$. □

In higher dimensions, the invertibility of Vandermonde matrices is not guaranteed. The problem of efficiently characterizing the invertibility of these matrices is a challenging open problem.

3. RECONSTRUCTION ALGORITHM

There are other general results for reconstructing bandlimited functions from sampling sets [4]. The purpose of the algorithm presented here is to assist with proving the stability estimates in Theorem 1. For $d > 1$, an iterative process can be used to determine unknown coefficients in (6).

Theorem 2. *The function $f \in \mathcal{B}(\Omega_{M,N})$ is uniquely reconstructed from samples $f(y), y \in X$, where X satisfies the assumption of Theorem 1, using the following procedure:*

Step 1.: *For each $j \in \mathcal{K}^d$, $f_j := S_{X_j} f$.*

Step 2.: *If $d = 1$, set $b := (f_0, \dots, f_P)$, $f^{m_d} := (V^{-1}b)_{m_d+P}$, $m_d \in \mathcal{M}^1$. Then, skip to Step 5.*

If $d \geq 2$, for each $j' \in \mathcal{K}^{d-1}$,

$$\begin{aligned} b_{j'} &:= (f_{(j',0)}, \dots, f_{(j',P)}) \\ f_{j'}^{m_d} &:= (V^{-1}b_{j'})_{m_d+P}, \quad m_d \in \mathcal{M}^1 \end{aligned}$$

Step 3.: *For $l = d - 1, \dots, 2$, and for all $j' \in \mathcal{K}^{l-1}, m' \in \mathcal{M}^{d-l}$,*

$$\begin{aligned} b_{j'}^{m'} &:= (f_{(j',0)}^{m'}, \dots, f_{(j',P)}^{m'}) \\ f_{j'}^{(m_l, m')} &:= (V^{-1}b_{j'}^{m'})_{m_l+P}, \quad m_l \in \mathcal{M}^1. \end{aligned}$$

Step 4.: *For each $m' \in \mathcal{M}^{d-1}$, define*

$$\begin{aligned} b^{m'} &:= (f_0^{m'}, \dots, f_P^{m'}) \\ f^{(m_1, m')} &:= (V^{-1}b^{m'})_{m_1+P}, \quad m_1 \in \mathcal{M}^1. \end{aligned}$$

Step 5.: *The reconstruction of f is given by the formula*

$$f(x) = \sum_{m \in \mathcal{M}^d} f^m(x) e^{2\pi i L_m \cdot x}.$$

Proof. If $d = 1$, then Lemma 4 guarantees the unique recovery of the coefficient functions $f^m(x) := c_m^\alpha(x), m \in \mathcal{M}^1$. Then, as in [3], f can be uniquely reconstructed using the formula

$$f(x) = \sum_{m \in \mathcal{M}^1} f^m(x) e^{2\pi i L_m x} \sum_{m \in \mathcal{M}^1} c_m(x) e^{2\pi i m N x}.$$

Suppose $d > 1$. For each $j \in \mathcal{K}^d$, define $f_j := S_{X_j} f$. Then, for each fixed $j' \in \mathcal{K}^{d-1}$ and $k_d \in \mathcal{K}^1$, the system of equations (18) corresponding to the functions $f_{(j', k_d)}$ can be expressed

$$(24) \quad f_{(j', k_d)}(x) = \sum_{m_d \in \mathcal{M}^1} \left(\sum_{n' \in \mathcal{M}^{d-1}} c_{(n', m_d)}^\alpha(x) e^{2\pi i L_{n'} \cdot j' \delta} \right) e^{2\pi i L_{m_d} k_d \delta}.$$

The system (24) is an invertible Vandermonde system with the unknowns

$$f_{j'}^{m_d}(x) := \sum_{n' \in \mathcal{M}^{d-1}} c_{(n', m_d)}^\alpha(x) e^{2\pi i L_{n'} \cdot j' \delta}, \quad m_d \in \mathcal{M}^1.$$

This process is then repeated for $l = d - 1, \dots, 2$. For each, $j' \in \mathcal{K}^{l-1}, k_l \in \mathcal{K}^1, m' \in \mathcal{M}^{d-l}$, the system of equations corresponding to $f_{(j', k_l)}^{m'}$ is

$$f_{(j', k_l)}^{m'}(x) = \sum_{m_l \in \mathcal{M}^1} \left(\sum_{n' \in \mathcal{M}^{l-1}} c_{(n', m_l, m')}^\alpha(x) e^{2\pi i L_{n'} \cdot j' \delta} \right) e^{2\pi i L_{m_l} k_l \delta},$$

which is an invertible Vandermonde system with the unknowns

$$f_{j'}^{(m_l, m')}(x) := \sum_{n' \in \mathcal{M}^{l-1}} c_{(n', m_l, m')}^\alpha(x) e^{2\pi i L_{n'} \cdot j' \delta}, \quad m_l \in \mathcal{M}^1.$$

In the final step, for each $m' \in \mathcal{M}^{d-1}$ and $k_1 \in \mathcal{K}^1$, the system of equations corresponding to $f_{k_1}^{m'}$ is

$$f_{k_1}^{m'}(x) = \sum_{m_1 \in \mathcal{M}^1} c_{(m_1, m')}^\alpha(x) e^{2\pi i L_{m_1} k_1 \delta},$$

which is an invertible Vandermonde system with the unknowns

$$f^{(m_1, m')}(x) := c_{(m_1, m')}^\alpha(x), \quad m_1 \in \mathcal{M}^1.$$

Then, f can be reconstructed using the formula

$$f(x) = \sum_{m \in \mathcal{M}} f^m(x) e^{2\pi i L_m \cdot x} \sum_{m \in \mathcal{M}} c_m(x) e^{2\pi i m N \cdot x}.$$

The reconstruction formula is unique due to the invertibility of the Vandermonde system in each step. $\square$

4. PROOF OF THEOREM 1

The proof of the main result involves an analysis of each step in the algorithm given in Theorem 2.

Proof. By Lemma (7), the following estimate holds for each $k \in \mathcal{K}^d$:

$$(25) \quad \|f_k\|_{L^2(\mathbb{R}^d)}^2 \leq \Delta^d \sum_{y \in X_k} |f(y)|^2 \leq \sum_{y \in X_k} |f(y)|^2.$$

The norm of the iterates can then be bounded in the second step,

$$\begin{aligned} \|b_{j'}\|_{L^2(\mathbb{R}^d)} &= \sum_{j_d \in \mathcal{K}^1} \|f_{(j', j_d)}\|_{L^2(\mathbb{R}^d)}^2, \\ \|f_{j'}^{m_d}\|_{L^2(\mathbb{R}^d)}^2 &\leq \|V^{-1}\|_2^2 \|b_{j'}\|_{L^2(\mathbb{R}^d)}^2 \quad m_d \in \mathcal{M}^1. \end{aligned}$$

In the third step, for $l = d-1, \dots, 2$, and for all $j' \in \mathcal{K}^{l-1}$, $m' \in \mathcal{M}^{d-l}$,

$$\begin{aligned} \|b_{j'}^{m'}\|_{L^2(\mathbb{R}^d)}^2 &= \sum_{j_l \in \mathcal{K}^1} \|f_{(j', j_l)}^{m'}\|_{L^2(\mathbb{R}^d)}^2 \leq \|V^{-1}\|_2^{2(d-l)} \sum_{(j_l, k') \in \mathcal{K}^{d-l+1}} \|f_{(j', j_l, k')}\|_{L^2(\mathbb{R}^d)}^2, \\ \|f_{j'}^{(m_l, m')}\|_{L^2(\mathbb{R}^d)}^2 &\leq \|V^{-1}\|_2^2 \|b_{j'}^{m'}\|_{L^2(\mathbb{R}^d)}^2. \end{aligned}$$

In Step 4, corresponding to each $m' \in \mathcal{K}^{d-1}$, the resulting estimates are

$$(26) \quad \|b^{m'}\|_{L^2(\mathbb{R}^d)}^2 = \sum_{j_1 \in \mathcal{K}^1} \|f_{j_1}^{m'}\|_{L^2(\mathbb{R}^d)}^2 \leq \|V^{-1}\|_2^{2(d-1)} \sum_{(j_1, k') \in \mathcal{K}^d} \|f_{(j_1, k')}\|_{L^2(\mathbb{R}^d)}^2,$$

$$(27) \quad \|c_{(m_1, m')}\|_{L^2(\mathbb{R}^d)}^2 \leq \|V^{-1}\|_2^2 \|b^{m'}\|_{L^2(\mathbb{R}^d)}^2, \quad m_1 \in \mathcal{M}^1.$$

Combining (25) and (27), and the reconstruction step,

$$\|f\|_{L^2(\mathbb{R}^d)}^2 = \sum_{m \in \mathcal{M}^d} \|c_m\|_{L^2(\mathbb{R}^d)}^2 \leq \|V^{-1}\|_2^{2d} \sum_{k \in \mathcal{K}^d} \|f_k\|_{L^2(\mathbb{R}^d)}^2 \leq \|V^{-1}\|_2^{2d} \sum_{y \in X} |f(y)|^2.$$

The upper bound in (4) is a result of Lemma 3, $\sum_{k \in \mathcal{K}^d} \sum_{y \in X_k} |f(y)|^2 \leq (2M+1)^d \|f\|_{L^2(\mathbb{R}^d)}^2$, and therefore $B = (2M+1)^d$. The lower bound in (4) is then given by $A = \|V^{-1}\|_2^{-2d}$. Using the identity $\|V^{-1}\|_2^2 = (2M+1)\|V^{-1}\|_\infty^2$ and Lemma 4 results in the estimate on the lower

bound in (4). In the case $N = 1$ and $\delta = 1/(2M + 1)$, Lemma 4 gives $\|V^{-1}\|_\infty = 1$, and then $A = B = (2M + 1)^d$. □

ACKNOWLEDGEMENTS

This work has benefited from valuable discussions with Bjorn Engquist, Kasso Okoudjou, and Haomin Zhou. This research was supported in part by NSF grants DMS-1317015, DMS-1344199, and Institut Mittag-Leffler.

REFERENCES

- [1] Hamid Behmard and Adel Faridani. Sampling of bandlimited functions on unions of shifted lattices. *Journal of Fourier Analysis and Applications*, 8:1–22, 2002.
- [2] Arne Beurling and Paul Malliavin. On the closure of characters and the zeros of entire functions. *Acta Mathematica*, 118(1):79–93, sep 1967.
- [3] Björn Engquist and Christina Frederick. Nonuniform Sampling and Multiscale Computation. *Multiscale Modeling & Simulation*, 12(4):1890–1901, dec 2014.
- [4] Adel Faridani. A generalized sampling theorem for locally compact abelian groups. *Mathematics of Computation*, 63(207):307–307, 1994.
- [5] Walter Gautschi. How (Un) stable are Vandermonde systems? *Asymptotic and computational analysis*, pages 193–210, 1990.
- [6] Karlheinz Gröchenig. Non-Uniform Sampling in Higher Dimensions: From Trigonometric Polynomials to Bandlimited Functions. In John J. Benedetto and Paulo J.S.G. Ferreira, editors, *Modern Sampling Theory*, chapter 7, pages 155–171. Birkhäuser, Boston, 2001.
- [7] A.J. Jerri. The Shannon sampling theorem-Its various extensions and applications: A tutorial review. *Proceedings of the IEEE*, 65(11):1565–1596, 1977.
- [8] H. J. Landau. Necessary density conditions for sampling and interpolation of certain entire functions. *Acta Mathematica*, 117(1):37–52, jul 1967.
- [9] H. J. Landau. Sampling, data transmission, and the Nyquist rate. *Proceedings of the IEEE*, 55(10):1701–1706, oct 1967.
- [10] Farokh A Marvasti. *Nonuniform sampling*. Kluwer Academic/Plenum Publishers, 2001.
- [11] Athanasios Papoulis. *Signal analysis*. McGraw-Hill, 1977.
- [12] Claude E. Shannon. Communication in the presence of noise. *Proceedings of the IRE*, 37(1):10–21, Feb. 1949.

E-mail address: cfrederick6@math.gatech.edu

SCHOOL OF MATHEMATICS, GEORGIA INSTITUTE OF TECHNOLOGY